

Programming your remote control Power/Volume

Search Method for your TV code:

1. Turn on the TV by pressing the Power button on the TV itself
2. On the remote control press the **TV BUTTON** once
3. Press and hold **Setup Button** until the TV button blinks twice, then **release Setup Button**
4. Type in **991** on the number pad of the remote
5. Aim the remote control at the TV and press the **Power Button** on the remote once
6. Press and Release the **CH+ button** repeating until the TV powers off
7. Press the **Power Button** on the remote. The TV should power back on
8. Press the **Setup button** once to store the code
 - A.) If the TV does not turn back on then slowly press the CH- button repeatedly to go back though the codes until the TV turns back on, then **Press Setup Button** once when TV turns back on.
9. **Press and Hold the Volume + button** on the remote control and check and see if the volume increases while holding the Volume + button. If not repeat steps 1-9 as there could be more than 1 code to operate your TV Brand
10. Press the **STB Button** on the remote to operate the Set Top Box. You should be able to adjust the volume on the TV with the remote in the Set Top Box (STB) mode

****** if this does not work to program your Venture remote to your TV please call technical support with the Make/Brand and Model of the equipment you are trying to control. They will have a list of the codes to help you program to the specific brand of equipment you have. 852-2224 Venture Vision Technical Support is available 24 hours a day 7 days a week. If they are unable to help you they will contact the local office and a service technician can come help program your remote under the Digital Maintenance Program. ******

Programming Master Power

To program remote to power both the Set Top Box (STB) and the TV on/off at the same time.

11. Press **STB**
12. Press **Setup** – flashes 2 times
13. Type in **995**
14. Press **Power** button
15. Press **TV** button
16. Press **STB** button
17. Press **Setup** Button –flashes 2 times
18. Press **Power**